

## REWIREABLE INLINE DIMMER

**These instructions should be read carefully and retained after installation by the end user for further reference and maintenance**

### SAFETY

- Installation of this product should only be carried out by a qualified electrician or competent person to the latest Building and current IEE Wiring Regulations (BS7671)
- Before installation/maintenance, ensure the lamp or table lamp is unplugged
- Do not overload this accessory or subject it to conditions outside its rating

NB: Failure to follow the above could result in damage to the dimmer and invalidate any warranty

Wire as shown in Fig 2




Fig 2

- Replace the front cover and 4 screws, plug in and check for correct operation

## OPERATING INSTRUCTIONS

### On/Off:

- To turn ON/OFF simply press and release the button. The dimming position will be retained.

### Dimming Up and Down:

- Press and hold the button for more than a second and the dimmer will increase or decrease the dimming level

## LOADING

- Incandescent lamps Max. 1-60W
- Dimmable LED Lamps Max. 1-25W\*
- \* Please consult lamp manufacturer for compatibility

## INSTALLATION

- Live and Neutral wiring on the lamp side of switch can be reversed, but not the IN and OUT direction
- **IN** - should be wired to the plug side (Mains in)
- **OUT** - should be wired to the lamp side (Mains out)

Please see Fig 1 and Fig 2 for wiring method

Remove all 4 screws on the rear of the dimmer switch and remove the front cover to access terminals.



Fig 1

## MINIMUM LEVEL SETTING:

To set the minimum level, plug in the lamp while holding down the ON/OFF button: the dimmer will enter the minimum dimming setting mode:

1. Release the On/Off button when the lamp reaches the desired level (it can be pressed again to lower the level if required)
2. When the required minimum level is reached, unplug the lamp and plug it back in again. The minimum level will now be set.

## WARRANTY

This product has a warranty of 1 year from date of purchase. Failure to install in accordance with the current edition of the IEE Wiring regulations (BS7671), improper use or removal of the batch codes will invalidate the warranty. If this product should fail within its warranty period it should be returned to the place of purchase for a free of charge replacement. ML Accessories does not accept responsibility for any installation costs associated with the replacement product. Your statutory rights are not affected. ML Accessories reserve the right to alter product specification without prior notice.