

## DISMANTLING PROCEDURE

This product should be dismantled for disposal when it reaches the end of its life. Ensure that the electrical supply is disconnected before removal from the installation. Consult a qualified electrician if in any doubt.

Product type:	Commercial Downlights
Product codes:	WWxxR
Dismantling procedure:	
<ol style="list-style-type: none"> <li>1. Remove the screws on the rear of the housing (rubber grommets must be removed to access those on the curved side of the fitting), this allows the diffuser to separate from the main body of the luminaire</li> <li>2. Unscrew and remove the reflector from the back of the diffuser, remove the glass</li> <li>3. Unscrew and remove the light source from the luminaire housing</li> <li>4. Cut the cable and pull it out of the cable gland</li> </ol>	
Product type:	Commercial Downlights
Product codes:	WWxxC
Dismantling procedure:	
<ol style="list-style-type: none"> <li>1. Remove the screws on the side of the housing and loosen the springs, this allows the centre part of the luminaire to be removed</li> <li>2. Remove the screw adjacent to the hinge, this allows the diffuser to be unscrewed from the main body of the luminaire</li> <li>3. Unscrew and remove the reflector from the back of the diffuser, remove the glass</li> <li>4. Lift the dome cover away from the light source</li> <li>5. Unscrew and remove the light source from the luminaire housing</li> <li>6. Cut the cable and pull it out of the cable gland</li> </ol>	
Recycling material:	
Luminaire housing	Metal
Reflector	
Screws	
Diffuser	Glass
Dome cover	Plastic
Light source	Electrical goods
Cable	
Driver	

*Advice from local recycling facilities should be sought as to specific types of waste which may be accepted.*