



INSTALLATION & MAINTENANCE MANUAL

TRKSUS

GENERAL INSTRUCTIONS

These instructions should be read carefully and retained after installation by the end user for future reference and maintenance.

These instructions should be used to aid installation of the following product:

TRKSUS

SAFETY

- This product must be installed in accordance with the latest edition of the IEE Wiring Regulations (BS7671) and current Building Regulations. If in any doubt, consult a qualified electrician
- Please isolate mains prior to installation or maintenance

INSTALLATION

- Unscrew the cable retainer from each of the ceiling fixings (see Fig. 1)



Fig. 1

- Using the ceiling fixing as a template, mark the location for, and drill the fixing holes ensuring not to infringe with any gas/water pipes or electrical cables. Fix the ceiling fixings to the ceiling using plugs and screws provided. The fixings should be the same distance apart as the holes in the track.
- Thread the cables through the cable retainers, and screw the cable retainers back into the ceiling fixings (see Fig. 2)



Fig. 2

- Secure the adjustment connectors to the track with the screws provided
- Pull each cable hanging from the ceiling fixings into one of the adjustment connectors until it appears out of the hole in the side (see Fig. 3)




Fig. 3

- The height of the track can be raised by pulling more cable through the adjustment connector; it can be lowered by pushing the on the spring-loaded end of the adjustment connector to release
- Once the desired height has been achieved, the cable may be trimmed to within 10mm of the hole in the adjustment connector and a hex key used to tighten the cable

GENERAL

This product should be recycled in the correct manner when it reaches the end of its life. Check local authorities for where facilities exist.

Clean with a soft dry cloth only, do not use aggressive cleaning products or solvents which may damage the product.

WARRANTY

This product has a warranty of 1 year from date of purchase. Failure to install this product in accordance with the current edition of the IEE Wiring Regulations (BS7671), improper use, or removal of the batch code will invalidate the warranty. If this product should fail within its warranty period, it should be returned to the place of purchase for a free of charge replacement. ML Accessories does not accept responsibility for any installation costs associated with the replacement product. Your statutory rights are not affected. ML Accessories reserve the right to alter product specification without prior notice.

SUPPLIED BY:
(UK)
ML ACCESSORIES LTD, UNIT E CHILTERN PARK,
BOSCOMBE ROAD, DUNSTABLE LU5 4LT,
WWW.MLACCESSORIES.CO.UK

(EU) AUTHORISED REPRESENTATIVE
SLV LIGHTING GROUP,
DAIMLERSTRASSE 21-23,
52531 ÜBACH-PALENBERG, GERMANY
EMAIL: EPREL@GROUP.SLV.COM
MADE IN CHINA

