



Smart IP66 13A 2G Outdoor Socket

CU9KW / OP9KW – Pairing

Adding Device to the SmartLife – Smart Living App:

1. Download the SmartLife - SmartLiving app (by Volcano Technology Limited) on Google Play or the App Store
2. Once the app has been downloaded, open the app and log in or sign up
3. Ensure Bluetooth is turned ON.
4. Press and hold the left switch for 5 seconds (until you get a fast flash; if you get a slow flash, press and hold the left switch again for 5 seconds)
5. Then tap on “+” Add device, the app should automatically detect the socket
6. Confirm your 2.4Ghz Wi-Fi network and enter the password; tap on “Next”; the socket should be added to the app.

If the above fails, then follow the steps below:

1. Tap ‘+’ icon and Select Add Device
2. Tap on “Electrical”, then tap on “Socket “
3. Tap on “Other Modes”, then tap on “Wi-Fi”
4. Tap on “Next” 3 times, then press and hold the left switch for 5 seconds (until you get a slow flash; if you get a fast flash, press and hold the left switch again for 5 seconds)
5. Tap on “Blink Slowly”
6. Confirm your 2.4GHz Wi-Fi network and enter the password
7. Tap on “Go to Connect”, then go to settings on your phone and tap on “Wi-Fi”
8. Connect your phone to “SmartLife-XXXX” hotspot
9. Go back to the SmartLife App
10. The socket should be added to the app.

Reset Procedure:

- Power ON the socket after it has been powered off for 10 seconds.
- Press and hold the left switch for 5 seconds

Troubleshooting Tips

- Ensure you are connecting to a 2.4 GHz Wi-Fi Network
- Move closer to the router during setup
- Reset the socket if pairing fails
- Clear the cache (Tap on “Me”, then “Settings” and then tap on “Clear Cache”) and restart the app if pairing fails