



INSTALLATION & MAINTENANCE MANUAL

LANTSS / LANTBK

GENERAL INSTRUCTIONS

These instructions should be read carefully and retained after installation by the end user for future reference and maintenance.

These instructions should be used to aid installation of the following products:

LANTSS / LANTBK


SAFETY

- This product must be installed in accordance with the latest edition of the IEE Wiring Regulations (BS7671) and current Building Regulations. If in any doubt, consult a qualified electrician
- Please isolate mains prior to installation or maintenance
- Check the total load on the circuit (including when this luminaire is fitted) does not exceed the rating of the circuit cable, fuse or circuit breaker
- Please note the IP (Ingress Protection) rating of this product when deciding the location for installation
- This product is Class I and must be earthed
- This product is IP23 rated

INSTALLATION

- Provide power to the point of installation. Suitable IP rated junction boxes should be used where required
- Remove the 2 baseplate screws on either side of the fitting
- Using the baseplate as a template, mark the location of the fixing holes, and drill the holes ensuring not to infringe with any joists, gas/water pipes or electrical cables
- Feed cable through the cable entry grommet and secure baseplate to chosen surface
- Connect Live (brown), Neutral (blue) and Earth (green/yellow) to the 3-way terminal block in the base of the fitting (see Fig. 1)

Fig. 1



Neutral (blue)
Earth (green/yellow)
Live (brown)

- Line up the fitting with the baseplate and fasten down the 2 baseplate screws
- Install an E27 lamp into the fitting (not supplied) ensuring not to exceed the 40W maximum rating
- Reposition diffuser back into place
- Switch on power and test for correct operation

GENERAL

Clean with a soft dry cloth only, do not use aggressive cleaning products or solvents which may damage the product.

Do not use any source of high-pressure washers to maintain or clean this luminaire.

This product is not suitable for installation in or near a coastal or marine environment.

This product is dimmable dependent on lamp type.

This product should be recycled in the correct manner when it reaches the end of its life. Check local authorities for where facilities exist.

WARRANTY

This product has a warranty of 2 years from date of purchase. Failure to install this product in accordance with the current edition of the IEE Wiring Regulations, improper use, or removal of the batch codes will invalidate the warranty. If this product should fail within its warranty period, it should be returned to the place of purchase for a free of charge replacement. ML Accessories does not accept responsibility for any installation costs associated with the replacement product. Your statutory rights are not affected. ML Accessories reserve the right to alter product specification without prior notice.

230V
50Hz

IP23



ML
ACCESSORIES LTD



**UK
CA**

CE



02

ML Accessories Limited LU5 4LT
www.mlaccessories.co.uk

INTERNATIONAL
CONTACT DETAILS



DCJUL21_V2